



PARTS DESCRIPTION LIST

SYMBOL	DESCRIPTION
C-1	Capacitor: .22 mfd; 200 V
C-2	Capacitor, Ceramic: 82 mmfd, 10%; 500 V
C-3, C-4	Capacitor: .022 mfd; 400 V
C-5, C-6	Capacitor: .1 mfd; 400 V
C-7	Capacitor, Electrolytic: 50 mfd; 50 V
C-8	Capacitor, Ceramic: 500 mmfd; 1500 V
C-10	Capacitor: .01 mfd; 600 V
C-11A, B	Capacitor, Electrolytic: Each section 40 mfd; 500 V
C-12A, B	Capacitor, Electrolytic: Each section 40 mfd; 450 V
P-1	Plug: 4 Male Contacts
R-1	Potentiometer, Composition: 500,000 ohms
R-2	Resistor, Composition: 1500 ohms, 10%; 1/2 W
R-3	Resistor, Composition: 220,000 ohms, 10%; 1/2 W
R-4	Resistor, Composition: 10,000 ohms, 10%; 1/2 W
R-5	Resistor, Composition: 68,000 ohms, 10%; 1/2 W
R-6	Potentiometer, Composition: 50,000 ohms
R-7	Resistor, Composition: 100,000 ohms, 10%; 1/2 W
R-8, R-9	Resistor, Composition: 40,000 ohms, 10%; 1/2 W
R-10	Resistor, Composition: 4700 ohms, 10%; 1/2 W
R-11, R-12	Resistor, Composition: 150,000 ohms, 10%; 1/2 W
R-13, R-14	Resistor, Composition: 470,000 ohms, 10%; 1/2 W
R-15	Resistor, Wirewound: 350 ohms, 10%; 10 W
R-16	Resistor, Composition: 2200 ohms, 10%; 1/2 W
R-17	Resistor, Composition: 100 ohms, 10%; 5 W
R-18, R-19	Resistor, Composition: 10,000 ohms, 10%; 1/2 W
R-20	Resistor, Wirewound: 2 ohms, tapped at 1 ohm
R-21	Resistor, Composition: 2200 ohms, 10%; 1/2 W
R-22	Resistor, Composition: 330 ohms, 10%; 1/2 W
R-23	Potentiometer, Composition: 1000 ohms
S-1	Switch, Slide: DPDT S-505-117
S-2	Switch, SPST: part of R-23 R-537-121
T-1	Transformer, Output T-508-116
T-2	Transformer, Power T-508-117

THE
FISHER
Audio Amplifier • Model 70-AZ
FIGURE 7