



中国·人民电器集团  
PEOPLE ELE. APPLIANCE GROUP CHINA

MINI CIRCUIT BREAKER

# RDX2-100 MINI CIRCUIT BREAKER

## APPLICATION

The product used to protect line-conductor and overload, and short-circuit of small sealed motors, is mainly for protection of circuits with AC 220V and 50/60Hz, and for unfrequent conversion under normal conditions as well. Its action can be as up to 22-pole with its only one pole volume and it can be used as a leakage breaker by assembling with leakage.

## SPECITICATIONS




RDX2-100 1P



RDX2-100 2P



RDX2-100 3P



RDX2-100 4P

Rated voltage	220~415V
Rated current	40, 50, 63, 80, 100A
Breaking capacity	10KA (IEC60947)
Mechanical and electrical life	6000 times
Width pole	27mm
According to standards	IEC60898, GB10963-89 BS 3871

Rated current (A)	Pole number (P)	Rated voltage (V)	Breaking capacity (A)
40	1	120	20000
		230/240	10000
		400/415	4000
50	2, 3, 4	230/240	20000
		400/415	10000
		440	6000

## DIMENSIONS

