


S2 RELAY SERIES

AXIAL STYLE REED RELAY



The S2 reed relay series from Cynergy3 has been developed for applications where PCB mounting is not possible.

The relay can be mounted using a variety of methods and orientations to suit particular applications. The terminal pins are flexible enough to allow bending for assembly into equipment.

Available with either a 10W or 50W contact in a pressurized reed switch or a 100VA contact in a vacuum reed switch.

Features

- Variable mounting options
- 10W, 50W and 100VA contact options
- Reliable reed switch contacts

Please refer to this document for circuit design notes:

<https://www.cynergy3.com/blog/reed-relay-application-notes>

SPECIFICATIONS

Contact	Condition	Units	S2-03P	S2-XXP	S2-XXE	
Material			Ruthenium	Rhodium	Rhodium	
Switch Atmosphere			Pressurized	Pressurized	Vacuum	
Isolation Across Contacts		Volts DC	200	500	1000	
Switching Power Max.	Resistive load	Watts	10	50		
Switching Power Max.	Resistive load	VA		70	100	
Switching Voltage DC Max.	Resistive load	Volts DC	200	350	350	
Switching Voltage AC Max.	Resistive load	Volts AC RMS	140	300	300	
Switching Current DC Max.	Resistive load	mA DC	250	700	1000	
Switching Current AC Max	Resistive load	mA AC RMS	250	500	1000	
Carry Current Max.		Amps DC/AC RMS	1	2.5	2.5	
Contact Capacitance Max.	Open	Pico Farad (pF)	0.3	0.5	0.5	
Initial Contact Resistance Max.	Nominal coil voltage	Milliohms (mΩ)	100	100	100	
Insulation Resistance		Ohms (Ω)	10E10	10E10	10E10	
Lifetime Operations	Hot switching resistive load	Operations 50% duty cycle	10E7 (12V DC, 4mA)	10E6 (350V DC, 1mA)	10E7 (500V DC, 1mA)	
	Dry switching	Operations 50% duty cycle	10E8	10E9		
Coil			3V	5V	12V	24V
Must Operate Voltage	20°C	Volts DC	2.25	3.7	9	19
Must Release Voltage	20°C	Volts DC	0.5	1	2	3
Operate Time Inc Bounce	20°C	Milliseconds	0.1	1.0	1	11
Release Time Inc Bounce	20°C	Milliseconds	0.07	0.5	0.5	0.5
Resistance	20°C	Ohms	250	160	1000	1000

Note. The operate / release voltage and coil resistance will change at a rate of 0.4% per degree C. Values are stated at room temperature (20 degrees C)


Relay	Condition	Units	S2-03P	S2-XXP	S2-XXE
Isolation Contact/Coil Min.		Volts DC		1000	
Operating Temperature Range		°C		-40 to +85	
Storage Temperature Range		°C		-40 to +125	

STANDARD PARTS

	Coil Voltage VDC	Switching Power	Isolation VDC	Switch Atmosphere
S2-03P	3	10W	200	Pressurized
S2-05P	5	70VA	500	Pressurized
S2-12P	12	70VA	500	Pressurized
S2-24P	24	70VA	500	Pressurized
S2-05E	5	100VA	1000	Vacuum
S2-12E	12	100VA	1000	Vacuum
S2-24E	24	100VA	1000	Vacuum

Custom versions can be made for particular applications. Please contact Sensata with your requirements.

DIMENSIONS



Datasheets provided by Sensata Technologies, Inc., its subsidiaries and/or affiliates ("Sensata") are solely intended to assist third parties ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, valuation, and judgment in designing Buyer's systems and products. Sensata datasheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular datasheet. Sensata may make corrections, enhancements, improvements, and other changes to its datasheets or components without notice. Buyers are authorized to use Sensata datasheets with the Sensata component(s) identified in each particular datasheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATASHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATASHEETS OR USE OF THE DATASHEETS, EXPRESS, IMPLIED, OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATASHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com. SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY, AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA

CONTACT US

Sensata Technologies
Jan Tinbergenstraat 80
7559 SP Hengelo
The Netherlands
1-508-236-3800
+44 (0)1202 897969
cynergy3.enquiries@sensata.com