

STR 90120	Sak	Hybrid-Z-IC	+12(±0,2)V, 2A, 50W	=18/5Pin	=TO-3P	-
STR 90150	Sak	Hybrid-Z-IC	+15(±0,2)V, 2A, 50W	=18/5Pin	=TO-3P	-
ST(s)		MOS-N-FET-d	=BSS 139 (SMD-Marking)	35	SOT-23	=BSS 139
STT 1	Say	UJT-P	30V,75mA,I _p <4µA, I _v >7mA, η=0,58...0,64, R _{bb} =8...20kΩ	7b	TO-92	2N2646, 2N4871
STV-2 H-O	Sak	Si-St	1,07...1,15V(7mA)			-
STV-2 H-W	Sak	Si-St	1,13...1,21V(7mA)			-
STV-3-G	Sak	Si-St	1,72...1,80V(7mA)	31a	D0-27	-
STV-3 H-G	Sak	Si-St	1,72...1,80V(7mA)			-
STV-3 H-O	Sak	Si-St	1,60...1,68V(7mA)			-
STV-3 H-W	Sak	Si-St	1,60...1,80V(7mA)			-
STV-3 H-Y	Sak	Si-St	1,66...1,74V(7mA)			-
STV-3-O	Sak	Si-St	1,60...1,68V(7mA)	31a	D0-21	-
STV-3-Y	Sak	Si-St	1,66...1,74V(7mA)	31a	D0-27	-
STV-4 H	Sak	Si-St	2,10...2,35V(7mA)			-
STV 0030	Tho	BICMOS-IC	SAT, Sound & Video Processor, 8-Bit DAC, I ² C-Bus	64-MP		-
STV 82	Tho	MOS-N-FET-e	VFET, P, 800V, 5,5A, 125W, 140/400ns	18p	TO-3P	BUZ 355...356, 2SK685, 2SK695
STV 102	Tho	MOS-N-FET-e	VFET, P, 1000V, 4,2A, 125W, 140/400ns	18p	TO-3P	BUZ 357...358, BUZ 380...381, 2SK685
STV 1389 AQ	Tho	DIG-IC	Digital Cable Transfer Driver	32-MP		-
STV 1601 A	Tho	Hybrid-IC	Serial Interface Transmission Encoder	37-PGA		-
STV 1602 A	Tho	Hybrid-IC	Serial Interface Transmission Decoder	37-PGA		-
STV 2100	Tho	LIN-IC	CTV, HA/VA & Luma/Chroma Processor, PAL	30-SDIP		-
STV 2102 Ä	Tho	LIN-IC	CTV, HA/VA & Luma/Chroma Processor, PAL	42-SDIP		-
STV 2110 A	Tho	LIN-IC	CTV, HA/VA & Luma/Chroma Processor, PAL/SECAM	42-SDIP		-
STV 3300	Tho	CMOS-IC	Digital Video Filtering & Dematrixing	52-PLCC		-
STV 5343	Tho	LIN/DIG-IC	Teletext Decoder, RAM Adress. ...64kB	40-DIP		-
STV 5343 S	Tho	LIN/DIG-IC	=STV 5343:Fig. >	42-SDIP		-
STV 5345	Tho	HCMOS-IC	Ttx Processor f. West-Europa, 8 Integr. Pages, I ² C	40-DIP		-
STV 5345 H		HCMOS-IC	=STV 5345: f. Ost-Europa/Eastern Europe	40-DIP		-
STV 5345 T		HCMOS-IC	=STV 5345: f. Europa & Türkei/Europe & Turkey	40-DIP		-
STV 5712	Tho	LIN-IC	SMD, VC, 2 Head Advanced FM Audio Rec/Play Amp	16-MDIP		-
STV 5715	Tho	LIN-IC	SMD, VC, 2 Head Advanced Rec/Play Amp	20-MDIP		-
STV 5722	Tho	LIN-IC	SMD, VC, 2 Head Rec/Play Amp	16-MDIP		-
STV 5726	Tho	LIN-IC	SMD, VC, 4 Head Rec/Play Amp	20-MDIP		-
STV 5730	Tho	LIN-IC	SMD, TV,VC, On-Screen Display, Multistandard	28-MDIP		-
STV 8438	Tho	D/A-IC	Video, 3 Channel, 8 Bit	42-SDIP		-
STV 9303	Tho	LIN-IC	CTV,TV, VA System, Pulse Driven VA Out, Ucc=35V	10-SIL		-
STV 9303 W		LIN-IC	=STV 9303: >	11-SILP		-
STV 9379	Tho	LIN-IC	CTV,TV, Flyback Gen., VA Out, Ucc=42V, I _o =1,5A	17/7Pin	TO-220/7	-
STV 9410(P)	Tho	CMOS-IC	CRT,LCD, Semi-Graphic Display Processor	20-DIP		-
STVHD 90	Tho	MOS-N-FET-e	VFET, P, 50V, 52A, 125W, 140/420ns	17p	TO-220	PRFZ 40
STZ 6.8 T	Rhm	Z-Di	SMD, Z, Dual, 6,47...7,14V, <40kΩ(5mA)	35f	SOT-23	-

SU

SU 111	Hfo	Si-N-Darl+Di	S P, 450/400V, 10A, 120W	23a	TO-3	BU 921...922, BU 931...932
SU 160	Hfo	Si-N	CTV-HA, 1500/700V, 5A, 12,5W(Tc=95°)	23a	TO-3	BU 208(A), BU 508(A), 2SD 350(A), ++
SU 161	Hfo	Si-N	TV-HA, 1500/700V, 2,5A, 10W(Tc=90°)	23a	TO-3	BU 205(A), BU 705, 2SC1922, 2SD818, ++
SU 165	Hfo	Si-N	S P, SN, 900/350V, 2,5A, 10W(Tc=90°)	23a	TO-3	BU205, BUW11A 23a
SU 167	Hfo	Si-N	S P, SN, 800/325V, 10A, 100W	23a	TO-3	S 2530 A 23a
SU 169	Hfo	Si-N	S P, SN, 1000/400V, 10A, 100W	23a	TO-3	S 2530 A 23a
SU 177	Hfo	Si-N	S P, 800/400V, 4A, 50W(Tc=50°)	23a	TO-3	BUW 11 A 18j
SU 178	Hfo	Si-N	S P, SN, 800/400V, 6A, 60W(Tc=50°)	23a	TO-3	BU 426 A 18j
SU 179	Hfo	Si-N	=SU 178: 1000/450V	23a	TO-3	BU 903 18j
SU 180	Hfo	Si-N	S P, 1200/400V, 4A, 50W(Tc=50°)	23a	TO-3	BU 903 23a
SU 186	Hfo	Si-N	S P, SN, 160/125V, 15A, 150W	23a	TO-3	
SU 187	Hfo	Si-N	=SU 186: 250/200V	23a	TO-3	
SU 188	Hfo	Si-N	=SU 186: 300/250V, 20A	23a	TO-3	
SU 189	Hfo	Si-N	S P, SN, 850/400V, 15A, 175W	23a	TO-3	
SU 190	Hfo	Si-N	=SU 189: 1000/450V	23a	TO-3	
SU 191	Hfo	Si-N	S P, SMPS, 120/90V, 30A, 150W	23a	TO-3	
SU 192	Hfo	Si-N	S P, SMPS, 160/125, 25A, 150W	23a	TO-3	
SU 193	Hfo	Si-N	S P, SMPS, 300/250, 15A, 150W	23a	TO-3	
SU 310	Hfo	Si-N-Darl	S P, SMPS, 200/150, 12A, 125W	23a	TO-3	
SU 311	Hfo	Si-N-Darl	S P, SMPS, 450/400, 12A, 125W	23a	TO-3	
SU 312	Hfo	Si-N-Darl	S P, SMPS, 450/400, 12A, 125W	23a	TO-3	
SU 377	Hfo	Si-N	S P, SN, 600/300V, 6A, 85W	17j	TO-220	BUT 56 A 17j
SU 378	Hfo	Si-N	S P, SN, 700/400V, 8A, 85W	17j	TO-220	BUT 56 A 17j
SU 379	Hfo	Si-N	=SU 377: 800/400V	17j	TO-220	BUT 56 A 17j
SU 380	Hfo	Si-N	=SU 378: 850/400V	17j	TO-220	BUT 56 A 17j
SU 382	Hfo	Si-N	S P, SMPS, 700/450V, 9A, 120W	18j	TO-3P	BUW 13 A 18j
SU 383	Hfo	Si-N	=SU 382: 850/450V	18j	TO-3P	BUW 13 A 18j
SU 384	Hfo	Si-N	=SU 382: 1000/450V	18j	TO-3P	BU 908 18j
SU 386	Hfo	Si-N	S P, SMPS, 160/125V, 15/20A, 150W	18j	TO-3P	
SU 387	Hfo	Si-N	S P, SN, 250/200V, 15/20A, 150W	18j	TO-3P	
SU 388	Hfo	Si-N	S P, SMPS, 300/250V, 20/25A, 150W	18j	TO-3P	
SU 389	Hfo	Si-N	S P, SMPS, 850/400V, 15/30A, 150W	18j	TO-3P	
SU 390	Hfo	Si-N	=SU 389: 1000/450V	18j	TO-3P	
SU 391	Hfo	Si-N	S P, SMPS, 125/90V, -/30A, 150W	18j	TO-3P	
SU 392	Hfo	Si-N	S P, SMPS, 160/125V, -/25A, 150W	18j	TO-3P	
SU 393	Hfo	Si-N	S P, SMPS, 300/250V, -/20A, 150W	18j	TO-3P	
SU 508	Hfo	Si-N-Darl+Di	S-L (380V=), 750/600V, 30A, 250W			-
SU 509	Hfo	Si-N-Darl+Di	S-L (380V=), 900/700V, 30A, 250W			-
SU 510	Hfo	Si-N-Darl+Di	S-L (380V=), 1000/800V, 30A, 250W			-
SU 518	Hfo	Si-N-Darl+Di	S P, SMPS, 600/600V, 60A, 160W			-
SU 519	Hfo	Si-N-Darl+Di	S P, SMPS, 900/800V, 60A, 160W			-
SU 520	Hfo	Si-N-Darl+Di	S P, SMPS, 1000/800V, 60A, 160W			-
SUF 4001	Sym	Si-Di	FRr, 50V, 1A, U _r <1V(1A), <50ns	31a	D0-41	BYV 27/200 31a
SUF 4002	Sym	Si-Di	=SUF 4001: 100V	31a	D0-41	BYV 27/200 31a
SUF 4003	Sym	Si-Di	=SUF 4001: 200V	31a	D0-41	BYV 27/200 31a
SUF 4004	Sym	Si-Di	=SUF 4001: 400V	31a	D0-41	BYV 26B...E, EGP 10G, FE 1H
SUF 5400	Sym	Si-Di	FRr, 50V, 3A, U _r <1V(3A), <50ns	31a	D0-27A	BYV 28/200 31a
SUF 5401	Sym	Si-Di	=SUF 5400: 100V	31a	D0-27A	BYV 28/100, EGP 30B...G, FE 3B...H
SUF 5402	Sym	Si-Di	=SUF 5400: 200V	31a	D0-27A	BYV 28/200, EGP 30D...G, FE 3D...H
SUF 5403	Sym	Si-Di	=SUF 5400: 300V	31a	D0-27A	EGP 30F...G, FE 3F...H